

105U-L-T/R One-Way I/O Pair

Wireless Input/Output Transmitter and Receiver



Description

The ELPRO 105U-L-T (Transmitter) and 105U-L-R (Receiver) products feature a small I/O count, one-way and cost-effective communications between field devices.

The 105U-L series products are flexible by design (i.e., pre-configured pairs for ease of commissioning) and may be used in simple to complex, multi-hop repeating networks (in combination with other ELPRO I/O and gateway products).

Features

- 869.525MHz/500mW or 869.875MHz/5mW frequency options.
- Flexible usage: pre-configured matched transmitter/receiver pair or complex networks via ELPRO I/O and/or Gateway products.
- Peer-to-peer communications with exception reporting, self-checking of messages via CRC, update time and secure data encryption.
- Multi-hop repeatability via ELPRO multi-I/O & Gateways products.

Transmitter Features

- 2 DI/PI (digital inputs can be pulse inputs), 1 AI (4-20mA), 1 TC (thermocouple input -10 - 100mV).
- 1 AI 24Vdc, 30mA analog loop supply capable.
- Additional internal inputs: set point (analog), power supply voltage.

Receiver Features

- 3 DO (relay outputs), 1 AO (0-20mA/4-20mA).
- Communications failure indication via configurable output.
- Receive radio signal strength indication using LEDs.

Applications

- Flow meter monitoring
- Storage tank monitoring
- Pipeline cathodic protection
- Pump stop-start
- Lighting bank control
- Emergency shower notification
- Weather station reporting
- Bearing condition monitoring
- Power reticulation relay fault notifications

Specifications	
Transmitter/Receiver	
Modulation	DFSK ⁽¹⁾ , 869.525MHz; 869.875MHz
Transmit Power	869.525MHz: 500mW; 869.875MHz: 5mW
Receiver Sensitivity	-111dBm (RX only)
Data Rate	19.2kbps with forward-error correction
Line Of Sight Range ⁽²⁾	500mW-5km out of plant: 1km in obstructed environments 5mW-1km out of plant: 300m in obstructed environments
Antenna Connector	SMA female coaxial
Transmitter Input	
Digital Input ⁽³⁾	2 (Voltage free contacts/NPN or 0-1Vdc on/>3Vdc off)
Pulse Input ⁽³⁾	2 (Max pulse rate 10Hz, pulse width 50ms: 16 bit resolution)
Analog Input	1 (0-20mA) floating differential input: 16 bit resolution, accuracy <0.1%
Thermocouple Input	1 (-10mV to +100mV, J, K or T type linearization; on-board cold-junction compensation: accuracy better than 1°C)
Receiver Output	
Digital Output	3 - DO relay outputs (250Vac/1A, 50Vdc/1A); (2500V RMS Isolated)
Analog Output	Sourcing current output 1 (0-20mA: 12 bit resolution, accuracy 0.1%)
Serial Port - Configuration Port Only	
RS232	9600 baud, 8 bit, no parity, 1 stop bit Note: RJ-45 connector is wired as per 9 pin female RS232 connector
Note: Specifications subject to change.	
1) DFSK - Digital Frequency Shift Keying.	
2) Actual radio distances dependent on terrain/obstacles.	
3) Pulse and digital I/O are the same connection.	
Continued on back.	

105U-L-T/R One-Way I/O Pair

Wireless Input/Output Transmitter and Receiver

Specifications	
LED Indication - Transmitter	
OK	Green: DC power OK, micro processor/module OK Red: system failure (power/micro processor/module failure)
DIN1	Digital input active/in use
DIN2	Digital input active/in use
SP	Setpoint status/active
TX	Radio transmitting
AZ	Analog value zero
PG	Program mode (unit communicating with laptop/computer)
SET	Pre-define setpoint selection
LED Indication - Receiver	
OK	Green: DC power OK: micro processor/module OK Red: system failure (power/micro processor/module failure)
D01	Digital output active/in use
D02	Digital output active/in use
D03	Digital output active/in use
Radio RX	Radio receiving
CF	Communications failure
PG	Program mode (unit communicating with laptop/computer)
Sig	RSSI level display
General	
Size	3.9" x 0.9" x 4.7" (100 x 22 x 120mm)
Weight	0.6lbs (275g)
Temperature	-40 to +60°C (-40 to 140°F)
Humidity	0-99%RH Non-Condensing
Housing	PC/ABS Plastic
Mounting	DIN rail mounting
Terminal Strip	Removable: up to 2.5mm ² (12AWG)
Approvals	EMC: EN 301 489 Radio: EN 300 220 Safety: EN 60950, ATEX Zone 2, IECEx nA IIC
Power Supply	
Nominal Supply	9 - 30Vdc
Quiescent Current	40mA Transmitter 40mA Receiver
Transmission Current	200mA Tx (500mW), 90mA Tx (5mW)
Note: Specifications subject to change.	

Ordering

To order, select product code from the table and specify country of application.

Product Code	Description	Frequency	RF Power
EL-105U-L-R-868-500M	Receiver, 3 DO, 1 AO	869.525MHz	500mW
EL-105U-L-R-868-5M	Receiver, 3 DO, 1 AO	869.875MHz	5mW
EL-105U-L-T-868-500M	Transmitter, 2 DI/PI, 1 AI, 1TC	869.525MHz	500mW
EL-105U-L-T-868-5M	Transmitter, 2 DI/PI, 1 AI, 1TC	869.875MHz	5mW
EL-105U-L-P1	Kit 105U-L-T, 105U-L-R 2 x DG800-1 Whip Antenna Configuration Cable	869.525MHz	500mW
EL-105U-L-P2	Kit 105U-L-T, 105U-L-R 2 x CFD890EL Dipole Antenna Configuration Cable	869.525MHz	500mW

Note: Available RF power and frequency may vary depending on country of application.

Accessories

The following accessories can assist with compatibility when commissioning.

Product Code	Description	Data Sheet #
Antennas - 868MHz		
CFD890EL	Dipole Antenna - SMA Male, 0dBi gain, 5m Coaxial cable, mounting bracket	7942
SG900EL	Collinear Antenna - N-type Female, 5dBi gain	7942
SG900-6	Collinear Antenna - N-type Female, 8dBi gain	7942
WH900-SMA	Demo Whip Antenna - 100mm long, SMA Male, -2dBi	7942
DG800-1	Whip Antenna - SMA Male, -2dBi gain, 2m RG174, bracket	7942
DG800-5	Whip Antenna - SMA Male, -5dBi gain, 5m RG174, bracket	7942
YU6/16-870	Yagi Antenna - 6/16 element, N-type, 10/15dBi gain	7942
Cables		
CC3/10/20-SMA	Coaxial Cable Kit - 3m/10m/20m, N-type to SMA	7932
CCTAIL-SMA-F/M	Coaxial Cable Tail - 600mm, SMA to N-type Female or SMA to N-type Male	7932
SER-RJ45	Configuration Cable - RS232 Serial, DB9 Female to RJ45	7932
Surge Diverters		
CSD-SMA-2500	SMA Surge Diverter for use with CC10, CC20 - SMA	7936
CSD-N-6000	Coaxial Surge Divertor, Bulkhead N Female to N Female	7936
IOP32/IOP32D	Signal Surge Diverter, 2 wire/4 wire	7936
Power Supplies		
PS-DINAC-12DC	DIN Rail Power Supply, 100 - 250Vac, 12Vdc/2.5A	7935
PS-DINAC-24DC	DIN Rail Power Supply, 100 - 250Vac, 24Vdc/2A	7935

The only controlled copy of this Data Sheet is the electronic read-only version located on the Cooper Bussmann Network Drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Cooper Bussmann reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Cooper Bussmann also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.