



Viola M2M Gateway User Manual

Viola M2M Gateway (2500)



Firmware Version 2.4
Document Version 4.0
October 2010

Copyright and Trademark

Copyright © 2008-2010, Viola Systems Ltd. All rights to this manual are owned solely by Viola Systems Ltd. (referred elsewhere in this User's Manual as Viola Systems). All rights reserved. No part of this manual may be transmitted or reproduced in any form or by any means without a prior written permission from Viola Systems.

Ethernet™ is a trademark of XEROX Corporation. Windows™ and Internet Explorer™ are trademarks of Microsoft Corporation. Netscape™ is a trademark of Netscape Communications Corporation. All other product names mentioned in this manual are the property of their respective owners, whose rights regarding the trademarks are acknowledged.

Viola Systems Ltd.

Lemminkäisenkatu 14-18 A

FI-20520 Turku

Finland

E-mail: info@violasystems.com

Technical Support

Phone: +358 20 1226 226

Fax: +358 20 1226 220

E-mail: support@violasystems.com

Internet: <http://www.violasystems.com>

Disclaimer

Viola Systems reserves the right to change the technical specifications or functions of its products or to discontinue the manufacture of any of its products or to discontinue the support of any of its products without any written announcement and urges its customers to ensure that the information at their disposal is valid.

Viola software and programs are delivered “as is”. The manufacturer does not grant any kind of warranty including guarantees on suitability and applicability to a certain application. Under no circumstance is the manufacturer or the developer of a program responsible for any damage possibly caused by the use of a program. The names of the programs as well as all copyrights relating to the programs are the sole property of Viola Systems. Any transfer, licensing to a third party, leasing, renting, transportation, copying, editing, translating, modifying into another programming language or reverse engineering for any intent is forbidden without the written consent of Viola Systems.

Viola Systems has attempted to verify that the information in this manual is correct with regard to the state of products and software on the publication date of the manual. We assume no responsibility for possible errors which may appear in this manual. Information in this manual may change without prior notice from Viola Systems.

Declaration of Conformity

(according to ISO/IEC Guide 22 and EN 45014)

Manufacturer's Name: Viola Systems Ltd.

Manufacturer's Address:

Lemminkäisenkatu 14-18 A

FI-20520 Turku

Finland

declares that this product:

Product Name:

Viola M2M Gateway

conforms to the following standards:

EMC:

EN 55022 Emission Test (Class A)

1. Radiated Emissions (30-1000MHz)
2. Conducted Emissions (0.15-30MHz)

EN 50082-1 Immunity Test

1. IEC 801-3: Radio Frequency Electromagnetic Field
2. IEC 801-2: Electrostatic Discharge
3. IEC 801-4: Fast Transients, AC Power Ports and Signal cables

Supplementary Information:

"The product complies with the requirements of the Low Voltage Directive 73/23/EEC and EMC directive 89/336/EEC."



Warning!

This is a Class A product. In a domestic environment this product may cause radio Interference which may make it necessary for the user to take adequate measures.

Manufacturer's Contact Information:

Viola Systems Ltd.

Lemminkäisenkatu 14-18 A

FI-20520 Turku

Finland

Phone: +358 20 1226 226

Fax: +358 20 1226 220

Warranty and Safety Instructions

Read these safety instructions carefully before using the products mentioned in this manual:

Warranty will be void if the product is used in any way in contradiction with the instructions given in this manual or if the product has been tampered with.

The devices mentioned in this manual are to be used only according to the instructions described in this manual. Faultless and safe operation of the devices can be guaranteed only if the transport, storage, operation and handling of the devices is appropriate. This also applies to the maintenance of the products.

To prevent damage both the product and any terminal devices must always be switched OFF before connecting or disconnecting any cables. It should be ascertained that different devices used have the same ground potential. Before connecting any power cables the output voltage of the power supply should be checked.

This product is not fault-tolerant and is not designed, manufactured or intended for use or resale as on-line control equipment or as part of such equipment in any hazardous environment requiring fail- safe performance, such as in the operation of nuclear facilities, aircraft navigation or communication systems, air traffic control, direct life support machines, or weapons systems, in which the failure of Viola Systems manufactured hardware or software could lead directly to death, personal injury, or severe physical or environmental damage.

Revisions

Date	Document Version	Firmware Version	Description of changes
05/2004	1.0		Manual released
08/2004	2.0		
06/2008	3.0		
09/2010	4.0		Manual released

Contents

COPYRIGHT AND TRADEMARK	2
DISCLAIMER.....	3
DECLARATION OF CONFORMITY.....	4
WARRANTY AND SAFETY INSTRUCTIONS.....	5
REVISIONS.....	6
1. INTRODUCTION.....	9
1.1 About Viola M2M Gateway.....	9
1.2 M2M Gateway Features.....	9
1.3 Packaging information.....	10
1.4 Hardware description.....	10
1.4.1 Front panel.....	10
1.4.2 Back Panel.....	10
1.4.3 Product label.....	11
2. NETWORK REQUIREMENTS.....	12
2.1 Connection Principle.....	12
2.2 Minimum Network Requirements.....	12
2.3 Routing Setup.....	13
2.4 Other Network Services.....	13
2.5 Recommended Network Setup.....	13
2.6 Using the Second Ethernet Port.....	14
3. QUICK INSTALLATION.....	15
3.1 Setting IP Address Using Web Browser.....	15
4. NETWORK CONFIGURATION.....	18
4.1 Configuration screens.....	18
5. VPN CONNECTIVITY.....	19
5.1 VPN requirements.....	19
5.2 Available VPN types.....	19
5.3 Typical connection scheme.....	19
5.4 Typical connection scheme with routing.....	20
6. SSH-VPN CONFIGURATION.....	22
6.1 Introduction to SSH-VPN.....	22
6.2 SSH-VPN Configuration screen.....	22
6.3 Creating new connection.....	23
6.4 Checking connection.....	24
6.5 Finalising SSH-VPN setup.....	24
6.6 Editing existing connection.....	25
6.7 SSH port configuration.....	25
7. L2TP-VPN CONFIGURATION.....	26
7.1 Introduction to L2TP-VPN.....	26
7.2 L2TP-VPN configuration screen.....	26
7.3 Creating new connection.....	27
8. OPENVPN CONFIGURATION.....	28

9. ADDITIONAL SYSTEM CONFIGURATION.....	29
9.1 Changing system password.....	29
9.2 Firewall.....	29
9.2.1 Firewall configuration screen.....	29
9.2.2 Changing firewall rules.....	30
9.3 Date and time.....	30
9.3.1 Manual configuration.....	31
9.3.2 Automatic configuration with NTP.....	31
9.4 Backup.....	31
9.4.1 Backup screen.....	31
9.4.2 Creating backups.....	32
9.4.3 Restoring backups.....	32
9.4.4 Moving backups between units.....	32
9.5 System logs.....	33
9.6 Supportlog.....	33
9.7 Factory default settings.....	34
10.ADVANCED SETTINGS.....	35
10.1 Command Line Shell.....	35
10.2 Advanced UI Menus.....	35
10.2.1 System menu.....	35
10.2.2 Networking menu.....	35
10.2.3 Others menu.....	35
11.TROUBLESHOOTING.....	37
12.SPECIFICATIONS	38
13.LIMITED WARRANTY.....	39
14.TECHNICAL SUPPORT	40


1 Introduction

This document describes how to configure the Viola M2M Gateway product.

1.1 About Viola M2M Gateway

The Viola M2M Gateway is a network device that enables VPN connection between company network and remote Arctic devices. It can also be used to control and monitor Arctic devices in local or remote networks. Concept of the Viola M2M Gateway is described in figure 1.

Figure 1. Viola M2M Gateway Concept



A computer with the network connection and an HTML browser is required to configure the M2M Gateway. Using the M2M Gateway Web user interface, you can configure and view the status of the remote Arctic devices and configure the VPN connection between M2M Gateway and Arctic device. Arctics have a WWW user interface which can be used to configure them using a HTML browser.

For the rest of this documentation, the Viola M2M Gateway is referred as M2M Gateway.

1.2 M2M Gateway Features

The M2M Gateway offers different advanced features for network usage. In most simple usage only VPN feature is used, but M2M Gateway makes possible to make complex network configurations.

Routing

M2M Gateway can forward packets to local Ethernet (eth0) which it is connected to company network. Also it is possible to route packets to second Ethernet (eth1) of M2M Gateway. More complex routing solutions can be made but they need consultation of your local network administrator.

Firewall

The M2M Gateway has internal firewall with graphical user interface. It is possible to connect M2M Gateway directly to the Internet and filter unwanted connections without external firewall. The recommended method is to use a dedicated firewall and install M2M Gateway behind it.

VPN

VPN is used to connect remote Arctic devices to local network. The connection is initiated by Arctic and the M2M Gateway decides based

on its configuration does it allow remote Arctic start VPN connection. VPN connection can be disabled from M2M Gateway. If the connection is terminated for some reason, it gets connected automatically by back up.

Remote Management

M2M Gateway offers full remote management. Also traditional console access is available using SSH.

1.3 Packaging information

The product package should contain the following items:

- Viola M2M Gateway
- Power cord
- Viola M2M Gateway Quick Start Guide

1.4 Hardware description

This section describes the front and back panel features of M2M Gateway.

1.4.1 Front panel

M2M Gateway front panel is shown in figure 2.

Figure 2. Front Panel




LEDs and switches (from left to right):

1. Temp LED, lit if system temperature is too high
2. Nic 2 activity LED (Eth 1 / LAN)
3. Nic 1 activity LED (Eth 0 / WAN)
4. HD activity LED
5. Power LED
6. Reset switch
7. Power switch

1.4.2 Back Panel

M2M Gateway back panel is shown in figure 3.

Figure 3. Back panel



Connectors (from left to right):

1. Power plug
2. Mouse and keyboard connector
3. USB connectors
4. Serial connector
5. Parallel connector
6. VGA display connector
7. Ethernet 0 connector (Eth0 / WAN)
8. Ethernet 1 connector (Eth1 / LAN)

1.4.3 Product label

Product label is found on the bottom of the device and it contains the basic information about the unit such as product name, serial number and Ethernet MAC address.

Figure 4. Product label



2 Network Requirements

M2M Gateway works properly when the required parameters which are described in this chapter are configured. For your network settings, contact your local network administrator.


Note!

Misconfiguration of the M2M Gateway can seriously hinder your network. Make sure you verify your network configuration with local network administrator.

2.1 Connection Principle

Company Intranet is normally connected to Internet via firewall. Figure 5 shows the M2M Gateway connected to the Demilitarized Zone (DMZ) of the firewall. This configuration allows hosts from Company Intranet to connect via firewall to the M2M Gateway. Other configurations are also possible.

Figure 5. DMZ Connection



Note!

It is possible that the internal routing in company intranet may require configuration in order to integrate M2M Gateway to an existing network.

2.2 Minimum Network Requirements

The M2M Gateway requires the following settings:

- One public IP address for M2M Gateway
- SSH port (default 22) unblocked for incoming connections to M2M Gateway from the remote network

Although this configuration is minimal, it can be used for testing and evaluating more complex systems. It is always recommended to consult local network administrator when installing new servers to the public network.

2.3 Routing Setup

When the M2M Gateway is installed to the existing network, some configuration is required to add the route to the M2M Gateway and devices behind it. For example, local firewall to router needs to be aware of routes going via the M2M Gateway. Routing can be complex to setup in large networks and it is recommend to consult local network administrator also about routing.

2.4 Other Network Services

M2M Gateway network services are listed in table 1. The only mandatory service is Secure Shell (SSH). SSH server listen to the incoming connections from Arctic devices in port 22 (default). This port must not be blocked by any firewall otherwise the remote Arctic devices are not able to open VPN connections to the M2M Gateway.

Arctic uses ICMP ECHO (ping) messages to check its network connection to the M2M Gateway. By default, the private IP address of the VPN peer is used as the target for the network connection status check. i.e. the M2M Gateway is not required to accept ICMP ECHO messages.

The network connection status check can also be made using some public IP address (e.g. the public IP address of the M2M Gateway). In this case the target host of the network connection check is required to accept ICMP ECHO messages and that they are not blocked by any firewall.

Table 1: Network Services

Service	Default Port	Protocol	Description
SSH	22	TCP	SSH-VPN tunnel, SSH remote access
ICMP ECHO	-	ICMP	Network connection checking
OpenVPN	1194	TCP / UDP	OpenVPN tunnel
L2TP	1701	1701	L2TP-VPN tunnel

Note!


Remote root user login is disabled for security reasons. User viola-adm must be used for SSH and web user interface logins.

2.5 Recommended Network Setup

The M2M Gateway is recommended to be connected to a DMZ of a firewall. This way the M2M Gateway can have public or private IP address depending on the firewall configuration. When placed in DMZ, the firewall protects efficiently against any unauthorized access to the M2M Gateway. Only incoming SSH connections are required to have access to DMZ zone. Services other than SSH are optional.

If the M2M Gateway is located in the DMZ and it has a private IP address, the firewall has to support port forwarding or destination network address translation (DNAT). For firewall configuration, please refer to your firewall documentation or to your local network administrator.


Figure 6. Recommended network setup



2.6 Using the Second Ethernet Port

If a firewall or network configuration does not allow the use of a DMZ or only few host has to have access to the M2M Gateway, the second Ethernet can be used. The second Ethernet of the M2M Gateway can be enabled from the Web user interface.. The IP address of the second Ethernet of the M2M Gateway is then used as the default gateway for the devices connected to the second Ethernet port.

Figure 7. Second Ethernet port in use



3 Quick Installation


This chapter describes how to configure the network interfaces on M2M Gateway.

3.1 Setting IP Address Using Web Browser

This section describes how to change factory default IP address for the first time.


1. Connect the cross-over Ethernet cable between Viola M2M Gateway (Ethernet 0 connector) and your configuration computer.
2. Configure your computer to use the same IP address space than Viola M2M Gateway (laptop IP for example 10.10.10.11 with netmask 255.0.0.0). Check with ping command.
3. Connect to the Viola M2M Gateway using your web browser. The default IP address of Viola M2M Gateway is 10.10.10.10 (netmask 255.0.0.0). Note that you have to connect to a HTTPS port 10000 (see figure 8).

Figure 8. Browser https example



4. Your browser might mention about certificates, you can safely ignore them at this point.
5. When you get to the login screen enter username and password and press Login button.

Figure 9. Login Screen




Note!

Default username is viola-adm and default password is violam2m. It is recommended that the default password is changed before the product is connected to a public network.

- Now you should be logged in and see a main configuration menu. Icons on the blue background are primary navigation icons and they are always visible on the screen. Icons lower are secondary navigation icons and clicking them allows the user to change the specific settings they represent. See figure 10.

Figure 10. Main Configuration Menu



- Select Network Configuration icon on the first page.
- From the next screen select Network Interfaces icon.
- Below the text "Interfaces Activated at Boot Time" select eth0.

Figure 11. Select eth0 interface

Interfaces Activated at Boot Time

Name	Type	IP Address	Netmask	Activate at boot?	Proxy ARP enabled?
eth0	Ethernet	172.16.6.2	255.255.0.0	Yes	No

- Enter your preferred configuration to the configuration fields.

Figure 12. Ethernet Configuration

Boot Time Interface Parameters

Name eth0	IP Address	<input type="radio"/> From DHCP	<input type="radio"/> From BOOTP	<input checked="" type="radio"/> Static
Netmask 255.255.0.0	<input type="text" value="172.16.6.2"/>	Broadcast <input checked="" type="radio"/> Automatic <input type="text"/>		
MTU <input checked="" type="radio"/> Automatic <input type="text"/>	Activate at boot?	<input checked="" type="radio"/> Yes <input type="radio"/> No		
	Enable Proxy ARP	<input type="radio"/> Yes <input checked="" type="radio"/> No		

11. Press Save and Apply button when you are ready to activate your new settings.

Note!

The existing web browser connection hangs up after you apply the settings, so open a new connection to the new IP address (check your Ethernet cabling)

12. Now you should be able to connect to the M2M Gateway with your new IP address.


4 Network Configuration

This chapter describes how to configure network interfaces on M2M Gateway.

4.1 Configuration screens

Network configuration screens can be found from main menu and pressing Network Configuration icon.

Figure 13. Network Configuration Menu



Network Interfaces

Displays running network configuration on the top on Interfaces Active Now list. This list contains all the interfaces running locally, including VPN interfaces. On the bottom there is a listing of physical interfaces (eth0 and eth1). Interface configuration can be changed by pressing underlined interface name. See figure 14.

Figure 14. Network Interface List

Interfaces Activated at Boot Time

Name	Type	IP Address	Netmask	Activate at boot?	Proxy ARP enabled?
<u>eth0</u>	Ethernet	172.16.6.2	255.255.0.0	Yes	No
<u>eth1</u>	Ethernet	172.30.30.1	255.255.255.0	Yes	No
<u>lo</u>	Loopback	127.0.0.1	255.0.0.0	Yes	No

Routing and Gateways

Configures default route, static routes and displays running routes. Default route can be changed from this screen. Enter the correct interface and IP address and press Save button.

Note!

Do not define more than one default route.

Hostname and DNS Client

Configures hostname and DNS settings.

Host Addresses

Shows hostnames assigned to IP addresses.

5 VPN connectivity

5.1 VPN requirements

VPN implementation on M2M Gateway requires:

- Open port in firewall for selected VPN server port
- Fixed IP address for M2M Gateway accessible from public Internet or used APN
- Remote client to connect to M2M Gateway (most commonly Viola Arctic product)
- Usually third node to monitor the connections and to access remote nodes (laptop, central management)

Note!

The M2M Gateway needs a fixed IP address.

5.2 Available VPN types

The available VPN types are L2TP, SSH and OpenVPN. A comparison is shown in table 2.

Table 2: VPN comparison table


VPN Type	Description	Encryptio	Default port
SSH-VPN	Default tunnel for Viola Arctic products	yes	22 TCP
L2TP-VPN	Lighter but less secure alternative to SSH-VPN	no	1701 UDP
OpenVPN	Best option for laptops and remote management	yes	1194 UDP

Selection of VPN depends on requirements, available link capacity and used hardware.

5.3 Typical connection scheme

Typical connection scheme is described in figure 15:

Figure 15. Typical VPN Connection




Network configuration in VPN tunneling will be easier if some rules are followed:

- Network addresses can not overlap, it is always best to use dedicated IP address range for VPN tunnels. Remember that VPN tunnel addresses are only visible between M2M Gateway and remote node.
- Netmasks should be strict to prevent network overlapping.
- Draw a network diagram with all the relevant information about the network you are building.

5.4 Typical connection scheme with routing

This example shows a little larger system. This common setup is practical in connecting remote networks to as a part of local network. This could be used to connect isolated remote stations to local monitor station.

Figure 16. Typical network setup with routing



The basic rules explained in the previous example are valid also in this example. Please take some time to browse the user interfaces of both M2M Gateway and Arctic to become familiar with the settings

Select routing mode to *Tunnel the following network*. IP address and netmask is the address that is located in the opposite side of the tunnel. For example, on Arctic set IP address to be the address that is assigned to the eth1 of M2M Gateway and vice versa.

6 SSH-VPN Configuration

This chapter describes how to use SSH-VPN module on Viola M2M Gateway.


6.1 Introduction to SSH-VPN

SSH-VPN uses SSH keys and remote nodes hostname to authenticate and validate remote connections. It is the default VPN for Viola Arctic products.

6.2 SSH-VPN Configuration screen

Configuration screen can be divided into different regions as shown below:


Figure 17. SSH-VPN configuration screen



- On the top are summary about peers and their last check.
- Configured connections are listed next. If the number of peers is over 500, list is divided to multiple pages. Below the list are connection test buttons.
- Key management field is located below peer list. Here are listed only those peers that do not have a key yet. If existing key for a peer needs to be changed, it must be done by editing the peer.
- On a bottom is SSH port configuration field.

Using action buttons on the peer list, the connections can be managed and monitored easily. See figure 18.

Figure 18. SSH-VPN Peer Listing

Peer	Interface	IP pair (m2mlP:peerIP)	Routing	Remote IP	Netmask	Status	Check
 pkc_arctic_test_1	ppp0	10.10.10.11 : 10.10.10.12	None			Active	n/a Disable Edit Remove

Possible actions are (from left to right):

1. Connectivity test selection box
2. Peer status icon (enabled or disabled)

3. Key status icon
4. Peer name
5. Interface assigned to peer
6. IP pair assigned to tunnel
7. Routing mode (none or network)
8. Remote IP if routing mode is set to network
9. Netmask if routing mode is set to network
10. Status (Active or Inactive)
11. Check status from last check (n/a, OK or Failed)
12. Enable/Disable button
13. Edit button
14. Remove button

6.3 Creating new connection

To configure a new connection:


1. Go to SSH-VPN configuration page.
2. Press Add peer button (located between peer list and key management box). See figure 17.
3. Enter values to fields. Required fields are peer name and IP pair. See figure 19.

Note!

Peer name must be same than hostname on Arctic.

4. Press Confirm button and return to previous screen.

Figure 19. SSH-VPN peer creation screen




After a new peer has been created, it will show up in peer list and its status will be disabled. To enable it, the keys must be exchanged between Viola M2M Gateway and Arctic. To do this:

5. Open Arctic user interface and SSH-VPN configuration screen on M2M Gateway to separate web browser windows.
6. On the Arctic, navigate to Network->SSH-VPN page.
7. Copy key from Arctic to M2M (see figure 6.4).
8. Select correct peer from list on M2M, paste Arctic key below and press Enter key button.

9. Copy M2M key from Server public key field.
10. Copy key from M2M to Arctic (see figure 20).

Figure 20. SSH-VPN key exchange



After the keys are exchanged, the peer can be enabled on the M2M Gateway. Just press Enable button on the peer list. Please note that the Arctic needs to be restarted before the connection comes up. After the Arctic restarts and connects, the peer status can be checked on the M2M by selecting a checkbox on the peer list and pressing Start check button.

For more information about configuring Arctic, refer to *Arctic User Manual*.

6.4 Checking connection

The Connection status displayed on SSH-VPN page does not update automatically, it has to be updated manually and the current status needs to be checked.

To check the current status of a peer:

1. Checked peers are selected by using checkboxes next to peer names. Peers can be selected individually or they all can be selected using *Check all* button.
2. Connection check is started by pressing *Start check* button. After the check is done, the results are displayed above the peer list (Checked n Peers -> n OK | n Failed date).
3. Results for individual peers can be seen on Check column on peer list.

Note!

Peer interface tells which interface is assigned to a peer. It is a local interface on M2M Gateway and it can not be used to determine the current connection status.

6.5 Finalising SSH-VPN setup


After all the peers have been configured, do the following:

1. Keys need to be locked. This can be done by pressing Lock keys button. This lock the keys and prevent their accidental deletion.
2. Create a backup. Instructions for this can be found in section 9.4.

6.6 Editing existing connection

Peers can be edited by selecting *Edit* button from the peer list. All the parameters except peer name can be changed from this edit screen. Note that the keys must be unlocked if keys need to be changed.

Figure 21. SSH-VPN Peer Edit screen



The screenshot shows the 'Edit peer' configuration screen. It contains the following fields and controls:

Peer name	arctic-2
Peer SSH key	1024 35 16364002716138956456783563565912601119081175203231731
IP pair (m2mIP:peerIP)	10.100.100.3 : 10.100.100.4
Routing mode	Tunnel the following network
Remote network IP	192.168.100.0
Remote network mask	255.255.255.0
Peer enabled?	Yes

At the bottom of the form are three buttons: Confirm, Cancel, and Remove SSH key.

6.7 SSH port configuration

Default port for SSH is 22. It is recommended to change this to something less common to increase system security. Changing SSH port on M2M Gateway is done by entering new port to a configuration field located in the bottom of the SSH-VPN configuration screen and pressing Change port button.

Note!

Changing the SSH port on M2M Gateway requires configuration changes to SSH-VPN connected Arctics as well. Also remote SSH access has to use new port.

7 L2TP-VPN Configuration


7.1 Introduction to L2TP-VPN

L2TP-VPN uses username and password to authenticate and validate remote connections. It is available on Viola Arctic products.

7.2 L2TP-VPN configuration screen

Configuration screen is shown in figure 22.

Figure 22. L2TP-VPN configuration screen



Using action buttons on the peer list, the connections can be managed and monitored easily. See figure 23. Possible actions are (from left to right):

Figure 23. L2TP-VPN peer listing

Peer	Interface	IP pair (m2mlP:peerP)	Routing	Remote ip	Netmask	Username	Password	Status	Check
<input checked="" type="checkbox"/>	ntp_test_peer (no IF)	10.2.2.21 : 10.2.2.22	None			ntp_test_peer	passwordhere	Active	n/a Disable Edit Remove

1. Connectivity test selection box
2. Peer status icon (enabled or disabled)
3. Peer name
4. Interface, available if peer is up
5. IP pair assigned to tunnel
6. Routing mode (none or network)
7. Remote IP if routing mode is set to network
8. Netmask if routing mode is set to network
9. L2TP username
10. L2TP password


- 11. Status (Active or Inactive)
- 12. Status (Active or Inactive)
- 13. Enable/Disable button
- 14. Edit button
- 15. Remove button

7.3 Creating new connection

To create new connection:

1. From the L2TP-VPN configuration screen, select *Add peer* button.
2. Fill in the settings for the tunnel. For simple point-to-point tunnel only peer name and IP pair are needed. Peer name is the hostname of the Viola Arctic that forms the other end of the tunnel. IP pair is an IP pair that does not conflict with any other address used. See figure 24.
3. Routing mode selects if the network on the other side of the tunnel is routed through the tunnel. Remote network IP and network mask define the remote network routed through the tunnel.
4. Username and password must be the same than on the Viola Arctic.
5. When you are done, press *Confirm* button to save the settings. The tunnel should now be added to the tunnel list.
6. Enable the tunnel by clicking *Enable* text.
7. The connection can be tested by selecting the checkbox next to the peer name and pressing the Start check button. See figure 22.

Figure 24. L2TP-VPN new peer



The screenshot shows a web-based configuration form titled "Add peer". The form contains the following fields and controls:

- Peer name:** A text input field.
- IP pair (m2mIP:peerIP):** Two text input fields separated by a colon.
- Routing mode:** A dropdown menu with "No routing" selected.
- Remote network IP:** A text input field.
- Remote network mask:** A text input field.
- Username:** A text input field with a yellow highlight.
- Password:** A text input field.
- Buttons:** "Confirm" and "Cancel" buttons at the bottom.

8 OpenVPN Configuration

Please refer to Viola Systems' OpenVPN application note.

9 Additional System Configuration


9.1 Changing system password

It is always recommended that the default password will be changed during the installation.

To change the password for user interface login:

1. From the top icon row on the blue background, select System icon.
2. From the System page select Change Passwords icon.
3. From the user list select user viola-adm.
4. Enter new system password and press Change to commit the new password. See figure 9.1.

Figure 25. Password change screen



The screenshot shows a web form titled "Changing Unix user password". Below the title, it says "Changing password for viola-adm". There are two text input fields: "New password" and "New password (again)". Below these are two checkboxes: "Force user to change password at next login?" (unchecked) and "Change password in other modules?" (checked). At the bottom are two buttons: "Change" and "Clear form".

The only users who can log in a system are viola-adm and root.

- User viola-adm is the only one who can log in to a web user interface.
- User root can log in only locally, remote root access is restricted.

9.2 Firewall

Firewall is an important part of the M2M Gateway product. Firewall should always be turned on and configured as strict as possible to keep out any unauthorized traffic.

Note!

It is not recommended to use M2M Gateway without firewall turned on if connected to any public network.


For more detailed explanation about firewall configuration, refer to application note *Configuring Viola M2M Gateway firewall*.

9.2.1 Firewall configuration screen

To reach the firewall configuration screen:

1. Login to M2M Gateway and enter the web user interface main menu.
2. From the top icon row on the blue background, select Networking icon.
3. From the Networking page select Linux Firewall icon.
The firewall configuration is divided into sections: Firewall has three chains (input, forward and output) which are listed separately.

Figure 26. Firewall Chain Listing




Action	Condition	Move	Add
Accept	If state of connection is ESTABLISHED	↓	↑ ↓
Accept	If state of connection is RELATED	↓ ↑	↑ ↓
Accept	If protocol is ICMP	↓ ↑	↑ ↓
Accept	If protocol is TCP and destination port is 22 and state of connection is NEW	↓ ↑	↑ ↓
Accept	If protocol is UDP and destination port is 53	↓ ↑	↑ ↓
Drop	If protocol is TCP and destination port is 80 and state of connection is NEW	↓ ↑	↑ ↓
Accept	If protocol is UDP and destination port is 1194:1199	↓ ↑	↑ ↓
Accept	If protocol is UDP and destination port is 1701	↓ ↑	↑ ↓
Accept	If protocol is TCP and destination port is 10000 and state of connection is NEW	↑	↑ ↓

Set Default Action To: Drop Clear All Rules Delete Selected Add Rule

On the bottom there are action buttons which can be used to apply or revert the changes.

Figure 27. Firewall Action buttons



Apply Configuration Click this button to make the firewall configuration listed above active. Any firewall rules currently in effect will be flushed and replaced

Revert Configuration Click this button to reset the configuration listed above to the one that is currently active.

Activate at boot Yes No Change this option to control whether your firewall is activated at boot time or not.

Reset Firewall Click this button to clear all existing firewall rules and set up new rules for a basic initial configuration.

9.2.2 Changing firewall rules

Default firewall rules allow only Arctic traffic. Rules can be changed in firewall configuration screen:

1. Existing firewall rules can be modified by clicking the Action text (colored Drop/Accept).
2. Adding new rules can be done by clicking the blue arrows on the left side of the rules.
3. Modified rules can be applied or old rules can be reset using the buttons at the end of the page.
The modified rules have to be applied by pressing *Apply Configuration* button before they are in use.

9.3 Date and time

It is important to have date and time set up correctly if certificate-based VPNs are in use.

To configure date and time:


1. Login to M2M Gateway and enter the web user interface main menu.
2. From the top icon row on the blue background, select System icon.
3. From the System page select System Time icon.
There are two methods to configure system time, manual and automatic with NTP protocol.

9.3.1 Manual configuration

To configure system time manually:

Enter time and date to system time and press *Apply*, then *Set system time to hardware time*.

Figure 28. Manual System Time Configuration



System Time				
Day	Date	Month	Year	Hour
Tuesday	24	June	2008	09 : 15 : 54
<input type="button" value="Apply"/>		<input type="button" value="Set system time to hardware time"/>		

Hardware Time				
Day	Date	Month	Year	Hour
Tuesday	24	June	2008	09 : 16 : 54
<input type="button" value="Save"/>		<input type="button" value="Set hardware time to system time"/>		


Time Zone	
Change timezone to	Europe/Helsinki
<input type="button" value="Save"/>	

9.3.2 Automatic configuration with NTP

To configure system time automatically with NTP protocol:

Enter valid ntp server address to timeserver field and press Sync and Apply button on the bottom of the screen.

Figure 29. Automatic System Time Configuration



Time Server	
Timeserver hostnames or addresses	<input type="text"/>
<input checked="" type="checkbox"/>	Set hardware time too


9.4 Backup

The Backup module saves user made settings of the Viola M2M Gateway. It backups configuration files and keys of VPN tunnels and firewall settings.

9.4.1 Backup screen

Backup screen can be found from the Web user interface main screen. Press Viola M2M Backup icon to open backup screen.


Figure 30. Backup Screen



9.4.2 Creating backups

From the first page select Viola M2M Backup icon and press create backup button to create a backup file. When the backup is created successfully, a notification text appears.


Figure 31. Backup created message



9.4.3 Restoring backups

Press open button to select the backup you want to restore and press restore backup button to restore the backup.

Figure 32. Backup Restore Selection



9.4.4 Moving backups between units

To restore a backup on a different machine, the backup file has to be copied into the /opt/viola/m2mBackups/ directory on the second machine. In addition, the MD5 file also has to be copied onto the new machine. This file has to be copied into the /opt/viola/MD5/ directory. After restoring the backup as described above, the IP address has to be changed to the IP address of


the machine the backup was created on. Afterwards the secondary unit can replace the primary unit seamlessly without any further configuration.

9.5 System logs

To reach the system logs:

1. Login to M2M Gateway and enter the web user interface main menu.
2. From the top icon row on the blue background, select System icon.
3. From the System page select System Logs icon.
Logs can be searched with defined text or just show last n entries.

Figure 33. System Log View




```
Last 20 lines of Only show lines with text Refresh
Jun 24 08:58:26 m2mgw sshd(pam_unix)[21914]: session closed for user viola-adm
Jun 24 09:00:51 m2mgw sshd(pam_unix)[21976]: session opened for user vvpn by (uid=0)
Jun 24 09:00:51 m2mgw logger: start_tunnel: starting VPN pkc_arctic_test_2
Jun 24 09:00:51 m2mgw logger: start_tunnel: ppp finished pkc_arctic_test_2
Jun 24 09:00:51 m2mgw pppd[21604]: Terminating on signal 15.
Jun 24 09:00:51 m2mgw sshd(pam_unix)[21558]: session closed for user vvpn
Jun 24 09:00:51 m2mgw pppd[21604]: Child process pppd (charshunt) (pid 21605) terminated with signal 15
Jun 24 09:00:51 m2mgw pppd[21604]: Modem hangup
Jun 24 09:00:51 m2mgw pppd[21604]: Connection terminated.
Jun 24 09:00:51 m2mgw pppd[21604]: Connect time 42.8 minutes.
Jun 24 09:00:51 m2mgw pppd[21604]: Sent 340 bytes, received 342 bytes.
Jun 24 09:00:51 m2mgw pppd[21604]: Connect time 42.8 minutes.
Jun 24 09:00:51 m2mgw pppd[21604]: Sent 340 bytes, received 342 bytes.
Jun 24 09:00:51 m2mgw pppd[21604]: Exit.
Jun 24 09:00:51 m2mgw logger: start_tunnel: killed old ppp pkc_arctic_test_2
Jun 24 09:00:51 m2mgw pppd[22023]: pppd 2.4.2 started by root, uid 0
Jun 24 09:00:51 m2mgw pppd[22023]: Using interface ppp0
Jun 24 09:00:51 m2mgw pppd[22023]: Connect: ppp0 <--> /dev/pts/0
Jun 24 09:00:52 m2mgw pppd[22023]: local IP address 10.10.10.21
Jun 24 09:00:52 m2mgw pppd[22023]: remote IP address 10.10.10.22
Last 20 lines of Only show lines with text Refresh
```

OpenVPN has its own logs which can be found from OpenVPN configuration.

9.6 Supportlog

Supportlog is a module that helps Viola Systems' technical support team in troubleshooting situations. It generates a collection of data from system that helps identifying the problem. It can generate a log package that can be e-mailed to Viola Systems' technical support. It is possible to collect all the data or smaller selection.

Figure 34. Supportlog Screen



Supportlog

This module creates supportlog reports from system and peer status and configuration. Select which reports to show below.

- Select all**
- SSHVPN interface status
- SSHVPN peer configuration
- SSHVPN keys and key status
- L2TP interface status
- L2TP peer configuration
- OpenVPN interface status
- OpenVPN peer configuration
- Ethernet information
- IP interface status and configuration
- IP routing status and configuration
- Open and established TCP and UDP connections
- Firewall status and configuration
- Firmware version
- Process list and CPU and memory usage
- System log, security log, tunnel log
- M2M backups status

9.7 Factory default settings

Factory default settings can be restored by selecting factoryBackup from backup restore selection screen. See section 9.4.

10 Advanced settings

These configuration options are targeted for advanced users only. Under normal operation these should not be changed.

10.1 Command Line Shell


The Connection status displayed on SSH-VPN page does not update automatically, it has to be updated manually and the current status needs to be checked.

10.2 Advanced UI Menus

10.2.1 System menu

- Bootup and Shutdown: change process and system level services on startup
- Bootup and Shutdown: change process and system level services on startup

Figure 35. System Menu




- SysV Init Configuration: inittab configuration (runlevels) for system startup
- System and Server Status: N/A, reserved for future use

10.2.2 Networking menu

- **SSH Server:** Advanced SSH server configurations. Under normal operation, only SSH port is changed from SSH-VPN user interface.
- **SSH/Telnet Login:** debugging console, not recommended for normal usage 28

Figure 36. Networking menu



10.2.3 Others menu

- **Command Shell:** debugging console for system level commands
- **Webmin Actions Log:** Web user interface access log data

Figure 37. Others Menu



11 Troubleshooting

This Chapter provides a list of the common problems encountered while installing, configuring or administering the Arctic. If you are unable to resolve your problem, refer to the Warranty and Technical Support Sections at the end of this User's Guide for information about contacting Viola Systems Technical Support representatives.

Q: When setting up routing mode "\tunnel the following network", routing to M2M Gateway eth1 does not work?

A: Check that IP forwarding has been enabled and internal firewall does not block packets.

Q: From Arctic Ethernet connection to M2M Gateway Ethernet is not working?

A: Check that IP forwarding has been enabled on Arctic.

Q: If only one public IP is available, can the M2M Gateway be used?

A: Yes, if firewall connected to public IP can forward incoming SSH connections to the M2M Gateway.

12 Specifications

Table 3: Technical specifications

Processor	Intel Celeron 2.5GHz
Memory	512Mb
Hard Drive	80Gb
Input voltage	100-240VAC (5A max)
Casing	Metal 19in rack mountable
Operating temperature	0 to 45 C
Storage temperature	-20 to +45 C
Humidity	10 to 90 % RH non-cond.
Network connection	2x Ethernet RJ-45 (10/100/1000 Base-T)
Approvals	CE, FCC

Technical specifications can be changed without notification.

13 Limited Warranty

Coverage

Viola Systems warrants this hardware product to be free from defects in materials and workmanship for the warranty period. This non-transferable, limited warranty is only to you, the first end-user purchaser. The warranty begins on the date of purchase and lasts for the period specified below:

Viola M2M Gateway : one (1) year

Excluded Products and Problems

This warranty does not apply to: (a) Viola Systems software products; (b) expendable components such as cables and connectors; or (c) third party products, hardware or software, supplied with the warranted product. Viola Systems makes no warranty of any kind on such products which, if included, are provided "AS IS." Excluded is damage caused by accident, misuse, abuse, unusually heavy use, or external environmental causes.

Remedies

Your sole and exclusive remedy for a covered defect is repair or replacement of the defective product, at Viola Systems' sole option and expense, and Viola Systems may use new or refurbished parts or products to do so. If Viola Systems is unable to repair or replace a defective product, your alternate exclusive remedy shall be a refund of the original purchase price.

The above is Viola Systems' entire obligation to you under this warranty. IN NO EVENT SHALL VIOLA SYSTEMS BE LIABLE FOR INDIRECT, INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES OR LOSSES, INCLUDING LOSS OF DATA, USE, OR PROFITS EVEN IF VIOLA SYSTEMS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. In no event shall Viola Systems' liability exceed the original purchase price of the device server. Some states or countries do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you.

Obtaining Warranty Service

You must notify Viola Systems within the warranty period to receive warranty service. During the warranty period, Viola Systems will repair or replace, at its option, any defective products or parts at no additional charge, provided that the product is returned, shipping prepaid, to Viola Systems. All replaced parts and products become the property of Viola Systems. Before returning any product for repair, customers are required to contact the Viola Systems.

14 Technical Support

Contacting Technical Support

Phone: +358 20 1226 226

Fax: +358 20 1226 220

E-mail: support@violasystems.com

Internet: <http://www.violasystems.com>

Recording Arctic Information

Before contacting our Technical Support staff, please record (if possible) the following information about your Arctic product:

Product name:

Serial no:

Note the status of your Arctic in the space below before contacting technical support. Include information about error messages, diagnostic test results, and problems with specific applications.
